



ELECTROHOME 103A & 104A

(PMU 51-417, 427)

PMU 51-437, 447)

ALIGNMENT—PROCEED IN SEQUENCE LISTED

Band	Dummy Antenna	Connect Generator To	Radio Dial Setting	Generator Frequency	Trimmer Adjusted	Adjustment	Approx. Sensitivity for 50 M.W. Output
1st I.F.	.05 Mfd.	Grid of 12SK7 Tube	1650 K.C.	455 K.C.	2nd I.F. C-12	Maximum Output	4000 Microvolts
Convertor Grid	.05 Mfd.	Grid of 12SA7 Convertor	1650 K.C.	455 K.C.	1st I.F. C-5	Maximum Output	100 Microvolts
B.C.	400 ohm.	Ant.	1460 K.C.	1460 K.C.	B.C. Osc. C-7 B.C. Ant. C-2	Maximum Output	30 Microvolts
B.C.	400 ohm.	Ant.	600 K.C.	600 K.C.			60 Microvolts

SENSITIVITIES

Sensitivity in microvolts for 50 milliwatts output (voice coil impedance 3.2 ohms) carrier modulated 30% at 400 cycles.

