



Electrohome

Serenader 505 Battery Operated Radio (SB1-4416)
Arcadia 446 Battery Operated Radio (MB1-4416)

ALIGNMENT—PROCEED IN SEQUENCE LISTED

Band	Dummy Antenna	Connect Generator To	Radio Dial Setting	Generator Frequency	Trimmer Adjusted	Adjustment
1st I.F.	.05 Mfd.	Grid of 1N5GT/G 1st I.F. Tube	1650 K.C.	455 K.C.	2nd I.F. C-6	Maximum Output
Converter Grid	.05 Mfd.	Grid of 1A7GT/G Converter	1650 K.C.	455 K.C.	1st I.F. C-5	Maximum Output
B.C.	200 mmfd.	Ant.	1400 K.C.	1400 K.C.	B.C. Osc. C-4 B.C. Ant. C-3	Maximum Output
B.C.	200 mmfd.	Ant.	600 K.C.	600 K.C.		Check Calibration Sensitivity

Electrohome Serenader 505 Battery Operated Radio (SB1-4416) Arcadia 446 Battery Operated Radio (MB1-4416)

