



Marconi Models 275, 275A

Marconi Models 275, 275A Alignment Procedure

CONNECT S.G. OUTPUT TO	INPUT FREQUENCY	RECEIVER DIAL SETTING	ADJUST	CIRCUIT RESONATED	REMARKS
*Stator Lug on Gang Capacitor R.F. Section	462.5 K.C.	Gang at Minimum	C9 - C8 C7 - C6	2nd I.F. 1st I.F.	MAXIMUM OUTPUT
***A & G	1720 K.C.	Gang at Minimum	C4	Osc.	MAXIMUM OUTPUT
A & G	1400 K.C.	1400 K.C.	C3	R.F.	MAXIMUM OUTPUT
A & G	580 K.C.	580 K.C.	OSC. CORE	OSC. (PAD)	ROCK GANG FOR MAXIMUM OUTPUT

* Apply signal through 0.1 Mfd. Condenser.
 ** Before proceeding with R.F. Alignment, see that pointer is set over last graduation mark on lower left end edge of dial backplate. Gang to be at maximum capacity.

