* A number of circuit changes were made on chassis of run No. 5 and above. This run number is rubber stamped in a star on the back of the chassis. Referring to Figs 2 and 3, the condenser m connects to the B- end of resistor m instead of to ground. The bucking coil - that section of m in series with the voice coil - is shorted out. The 10 mfd. dry electrolytic condenser m is eliminated, and replaced with a substitute .015 section combined with m, part 3793R. The .01 mfd. condenser m is eliminated. The positions of m m and m are changed in the

