



Phonola - Electrohme Z1T55-L, Z1T65-L, 1T55-P, 1T55-P-1, Z1TC55-P, Z1TC55-P-1 & Z1TC65-L

ALIGNMENT—PROCEED IN SEQUENCE LISTED.

Band	Band Switch Setting	Dummy Antenna	Connect Generator To	Radio Dial Setting	Generator Frequency	Trimmer Adjusted	Adjustment
2nd I.F.	B.C.	.1 Mfd.	Grid of 1S5K7 I.F. Tube	1650 K.C.	455 K.C.	2nd I.F. C-11	Maximum Output
1st I.F.	B.C.	.1 Mfd.	Grid of 1S5A7 Converter	1650 K.C.	455 K.C.	1st I.F. C-10	Maximum Output
1400 K.C.	B.C.	75 Mmfd.	Antenna	1400 K.C.	1400 K.C.	B.C. Osc. C-4 B.C. Ant. C-8	Maximum Output
600 K.C.	B.C.	75 Mmfd.	Antenna	600 K.C.	600 K.C.	Check	Maximum Output
40 Meters	40	250 Ohm	Antenna	6.10 M.C.	6.10 M.C.	6M.C. Osc. C-9 S.W. Ant. C-5	Maximum Output
31 Meters	31	250 Ohm	Antenna	9.55 M.C.	9.55 M.C.	9M.C. Osc. C-8	Calibration
25 Meters	25	250 Ohm	Antenna	11.85 M.C.	11.85 M.C.	11 M.C. Osc. C-7	Calibration
19 Meters	19	250 Ohm	Antenna	15.35 M.C.	15.35 M.C.	15 M.C. Osc. C-6	Calibration

Electrohome

- Z1T55-L
- Z1T65-L
- 1T55-P
- 1T55-P-1
- 1TC55-P
- Z1TC55-P
- 1TC55-P-1
- Z1TC55-P-1
- Z1TC65-L

