



NOTE:
ALL VOLTAGES MEASURED TO B-

WINDING POLARITY
"S" DESIGNATES START OF WINDING
"F" DESIGNATES FINISH OF WINDING

INDICATES CHASSIS CONNECTION ONLY

ALIGNMENT — PROCEED IN SEQUENCE LISTED.

Band	Band Switch Setting	Dummy Antenna	Connect Generator To	Radio Dial Setting	Generator Frequency	Trimmer Adjusted	Adjustment
2nd I. F.	B. C.	.1 Mfd.	Grid of 12SK7 I. F. Tube	1700 K. C.	455 K. C.	2nd I. F. C-10	Maximum Output
1st I. F.	B. C.	.1 Mfd.	Grid of 12SA7 Converter	1700 K. C.	455 K. C.	1st I. F. C-9	Maximum Output
1460 K. C.	B. C.	200 Mmfd.	Antenna	1460 K. C.	1460 K. C.	B. C. Osc. C-8 B. C. Ant. C-8	Maximum Output
600 K. C.	B. C.	200 Mmfd.	Antenna	600 K. C.	600 K. C.	B. C. Padder C-5	Maximum Output
16 M. C.	S. W.	400 Ohm	Antenna	15 M. C.	15 M. C.	S. W. Osc. C-8 S. W. Ant. C-4	Maximum Output
6 M. C.	S. W.	400 Ohm	Antenna	6 M. C.	6 M. C.	None	None

On our later models R15 was changed to 125 ohms.

*** NOTE:**
R15 MAY BE USED IN EITHER POSITION

115 V.A.C. - D.C.

**Phonola - Electrohome 40U52-E, 40U52E-1
40U52-P, 40U52P1, 40U52-L, 40U52-S &
40U52S-1**

