



Rogers 15-56A Majestic 4156A De Forest A65-41

(Chassis 10RA523)

ALIGNMENT DATA

Operation	Connect Generator	Set Generator Tuning	Set Receiver Tuning	Band Switch	Dummy Antenna	Vol. Cont.	Adjust	Remarks
1	To Grid Cap 20J8M Tube	456 kcs.	700-800 kcs.	Broadcast	.1 mfd.	Max.	C8, C9 C10, C11	To Peak I.F.
2	To Antenna	1600 kcs.	1600 kcs.	Broadcast	.0002 mfd.	Max.	C6	To Peak Osc.
3	To Antenna	1600 kcs.	1600 kcs.	Broadcast	.0002 mfd.	Max.	C4	To Peak Ant.
4	*To Antenna	600 kcs.	600 kcs.	Broadcast	.0002 mfd.	Max.	C7	To Track Osc.
5	To Antenna	1600 kcs.	1600 kcs.	Broadcast	.0002 mfd.	Max.	C6	To Check Osc.
6	To Antenna	17.5 mcs.	17.5 mcs.	Short-wave	400 ohms	Max.	C5	To Peak Osc.
7	To Antenna	17.5 mcs.	17.5 mcs.	Short-wave	400 ohms	Max.	C3	To Peak Ant.
8	To Antenna	17.5 mcs.	17.5 mcs.	Short-wave	400 ohms	Max.	C5	To Check Osc.

