



ALIGNMENT—PROCEED IN SEQUENCE LISTED

Band	Dummy Antenna	Connect Generator To	Radio Dial Setting	Generator Frequency	Trimmer Adjusted	Adjustment	Approx. Sensitivity for 50 M.W. Output
1st I.F.	.1 Mfd.	Grid of 12SK7 Tube	1650 K.C.	455 K.C.	2nd I.F. C-12	Maximum Output	4000 Microvolts
Converter Grid	.1 Mfd.	Grid of 12SA7 Converter	1650 K.C.	455 K.C.	1st I.F. C-6	Maximum Output	100 Microvolts
B.C.	200 Mmfd.	Ant.	1460 K.C.	1460 K.C.	B.C. Osc. C-7 B.C. Ant. C-2	Maximum Output	30 Microvolts
B.C.	200 Mmfd.	Ant.	600 K.C.	600 K.C.			14 Microvolts