



GANG		
12BE6	12BA6	35W4
	12AT6	50B5

STEP	APPLY SIGNAL AT KC	TO	THRU SERIES DUMMY	SET GANG AT	ADJUST FOR MAX. OUTPUT.	NOMINAL SENSITIVITY, 50 MILLI-WATTS OUTPUT AT 400 C/S.
1	455	1/2BA6 #12IN	.05	MINIMUM CAPACITY	2ND I.F.	2400 μ VOLTS
2	455	1/2BE6 #7DIN	.05	MINIMUM CAPACITY	1ST I.F. 2ND I.F.	70 μ VOLTS.
3	1460	ANT.	*	1460	OSC. TRIM ANT. TRIM.	130 μ V/M
4	1670	ANT.	*	MINIMUM CAPACITY	CHECK ONLY	120 μ V/M
5	600	ANT.	*	600	CHECK ONLY	400 μ V/M.
6	525	ANT.	*	MAXIMUM CAPACITY	CHECK ONLY	500 μ V/M

* FASHION LOOP OF SEVERAL TURNS OF WIRE AND RADIATE SIGNAL INTO LOOP OF RECEIVER. ADJUST FOR MAX. OUTPUT.