



No.	Control Grid to Filament	Screen Grid to Filament	Plate to Filament	Screen Current	Plate Current
		Volts		M.A.	
R.F.	0.2	65	157	1.0	3.0
1st Detector	0.5	65	157	0.1	0.2
Oscillator	1.0	65	65	4.0	4.0
I.F.	0.5	65	157	1.0	3.0
2nd Detector	2.0	155	0	4.0	0
1st A.F.	1.0	155	155	...	2.5
Power	14.0	155	155	...	1.2

TRIMMER ADJUSTMENTS

I.F.— 175 K.C. adjust in order—No. 1, No. 2, No. 3, No. 4
 R.F.—Trim at 1,400 K.C. in order—Osc., Det., R.F.
 Oscillator Tracking Condenser—Adjust at 600 K.C.

Marconi Model 32-B Battery Operated Radio