






Pilot Lamp Data

Maximum Size See Chart below for dimensions						
	Type No.	T-3 $\frac{1}{4}$	T-3 $\frac{1}{4}$	G-3 $\frac{1}{2}$	G-3 $\frac{1}{2}$	G-4 $\frac{1}{2}$
	Base	Screw (Miniature)	Bayonet (Miniature)	Screw (Miniature)	Bayonet (Miniature)	Bayonet (Miniature)
	Bulb	Tubular	Tubular	Small Round	Small Round	Large Round
	Lamp Numbers	40 41 42 46 48 292	40A 43 44 45 47 49 49A 292A	50	51	55

Lamp No.	Bead Color	Base (Miniature)	Bulb Type	RATING		Used for	Maximum Dimensions (See illustrations above)		
				Volts	Amps.		A	B	C
40	Brown	Screw	T-3 $\frac{1}{4}$	6-8	0.15	Dials.....	15 $\frac{1}{32}$ "	29 $\frac{1}{32}$ "	1 $\frac{1}{8}$ "
40A †	Brown	Bayonet	T-3 $\frac{1}{4}$	6-8	0.15	Dials.....	15 $\frac{1}{32}$ "	29 $\frac{1}{32}$ "	1 $\frac{1}{8}$ "
41	White	Screw	T-3 $\frac{1}{4}$	2.5	0.5	Dials.....	15 $\frac{1}{32}$ "	29 $\frac{1}{32}$ "	1 $\frac{1}{8}$ "
42	Green	Screw	T-3 $\frac{1}{4}$	3.2	‡	Dials.....	15 $\frac{1}{32}$ "	29 $\frac{1}{32}$ "	1 $\frac{1}{8}$ "
43	White	Bayonet	T-3 $\frac{1}{4}$	2.5	0.5	Dials and Tuning Meters.....	15 $\frac{1}{32}$ "	29 $\frac{1}{32}$ "	1 $\frac{1}{8}$ "
44	Blue	Bayonet	T-3 $\frac{1}{4}$	6-8	0.25	Dials and Tuning Meters.....	15 $\frac{1}{32}$ "	29 $\frac{1}{32}$ "	1 $\frac{1}{8}$ "
45	*	Bayonet	T-3 $\frac{1}{4}$	3.2	‡	Dials.....	15 $\frac{1}{32}$ "	29 $\frac{1}{32}$ "	1 $\frac{1}{8}$ "
46 ^	Blue	Screw	T-3 $\frac{1}{4}$	6-8	0.25	Dials and Tuning Meters.....	15 $\frac{1}{32}$ "	29 $\frac{1}{32}$ "	1 $\frac{1}{8}$ "
47 †	Brown	Bayonet	T-3 $\frac{1}{4}$	6-9	0.15	Dials.....	15 $\frac{1}{32}$ "	—	1 $\frac{1}{8}$ "
48	Pink	Screw	T-3 $\frac{1}{4}$	2.0	0.06	Battery Set Dials.....	15 $\frac{1}{32}$ "	29 $\frac{1}{32}$ "	1 $\frac{1}{8}$ "
49 §	Pink	Bayonet	T-3 $\frac{1}{4}$	2.0	0.06	Battery Set Dials.....	15 $\frac{1}{32}$ "	23 $\frac{1}{32}$ "	1 $\frac{1}{8}$ "
■	White	Screw	T-3 $\frac{1}{4}$	2.1	0.12	Dials.....	15 $\frac{1}{32}$ "	—	—
49A §	White	Bayonet	T-3 $\frac{1}{4}$	2.1	0.12	Dials.....	15 $\frac{1}{32}$ "	23 $\frac{1}{32}$ "	1 $\frac{1}{8}$ "
50	White	Screw	G-3 $\frac{1}{2}$	6-8	0.2	Auto-Radio Dials; Flashlights.....	1 $\frac{1}{2}$ "	23 $\frac{1}{32}$ "	15 $\frac{1}{16}$ "
51 ^	White	Bayonet	G-3 $\frac{1}{2}$	6-8	0.2	Auto-Radio Dials; Panel Boards...	1 $\frac{1}{2}$ "	1 $\frac{1}{2}$ "	15 $\frac{1}{16}$ "
—	White	Screw	G-4 $\frac{1}{2}$	6-8	0.4	Auto-Radio Dials; Flashlights.....	1 $\frac{1}{2}$ "	—	—
55	White	Bayonet	G-4 $\frac{1}{2}$	6-8	0.4	Auto-Radio Dials; Parking Lights..	5 $\frac{1}{8}$ "	1 $\frac{1}{2}$ "	11 $\frac{1}{16}$ "
292 °	White	Screw	T-3 $\frac{1}{4}$	2.9	0.17	Dials.....	15 $\frac{1}{32}$ "	29 $\frac{1}{32}$ "	1 $\frac{1}{8}$ "
292A °	White	Bayonet	T-3 $\frac{1}{4}$	2.9	0.17	Dials and Coin Machines.....	15 $\frac{1}{32}$ "	23 $\frac{1}{32}$ "	1 $\frac{1}{8}$ "
1455	Brown	Screw	G-5	18.0	0.25	Coin Machines.....	—	—	—
1455A	Brown	Bayonet	G-5	18.0	0.25	Coin Machines.....	—	—	—

* White in G.E. and Sylvania; Green in National Union Raytheon and Tung-Sol.

‡ 0.35 in G.E. and Sylvania; 0.5 in National Union Raytheon and Tung-Sol.

† **40A** and **47** are interchangeable.

§ **49** and **49A** are interchangeable.

^ Have frosted bulb.

■ Replace with No. **48**.

• Use in 2.5 volt sets where regular bulb burns out too frequently.