

SWAN

2-30 Mhz, up to 50 Mhz at slightly reduced accuracy

Design Impedance: 50 Ohm

Power Ranges:

1. 0 - 5 watts
2. 0 - 50 watts
3. 0 - 500 watts
4. 0 - 1500 watts

(Above ranges forward and reverse)

Meter: Reads forward or reverse power in watts

Accuracy: Better than + 10% of full scale

Directivity: Better than 30db

Insertion VSWR: 1.05:1 or less

SCHEMATIC DIAGRAM - MODEL WM-1500 WATTMETER



