

ALIGNMENT AND SENSITIVITY

SIGNAL GENERATOR MODULATED 30% AT 400 C.P.S.

APPLY SIGNAL AT KC.	TO	THRU SERIES DUMMY	SET GANG AT	ADJUST FOR MAX. OUTPUT	NOMINAL SENSITIVITY FOR 500 MILLIWATTS OUTPUT
455	#1 PIN	.05 μ fd.		2ND I.F. IRON CORES	3000 MICROVOLTS
455	#6 BEG #7 PIN	.05 μ fd.	1460	1ST I.F. 2ND I.F.	100
455	ANT.	200 μ fd.	OPEN	WAVE TRAP. MIN. OUTPUT	3000
1460	ANT.	200 μ fd.	1460	TWO GANG TRIMMERS	20
600	ANT.	200 μ fd.	600	B.C. OSC. PADDER	20
16 MC.	ANT.	400 Ω	16 MC.	S.W. OSC. ANT. TRIM.	40
10 MC.	ANT.	400 Ω	10 MC.	CHECK B.W.T.	40

SPECIFICATIONS

Standard Broadcast Range 540 Kc. - 1650 Kc.
 Short Wave Range 9.0 Mc. - 18.0 Mc.
 Intermediate Frequency 455 Kc.
 Power Consumption (Radio Only) 48 Watts
 Power Consumption (Radio & Phono) 65 Watts
 Undistorted Output 3.0 Watts
 Maximum Power Output 4.5 Watts

