



VIKING RM-542, RMK-543

ALIGNMENT		AND		SENSITIVITY		
SIGNAL		GEN	MODULATED	30 %	400 CYCLES	
STEP	APPLY SIGNAL	THRU SERIES DUMMY	SET GANG	ADJUST FOR MAX	SENSITIVITY FOR 50mw.	SENSITIVITY FOR 100mv DIODE LOAD
	KC					
1	455	12BA6 #1	MIN. CAP	2nd I.F	1200 uV	1850 uV
2	455	12BE6 #7	MIN CAP	1st I.F	48 uV	72 uV
3	1400	ANT.	1400	OSC. TRIM	—	—
4	1400	ANT	1400	ANT. TRIM	225 uV/M	390 uV/M
5	535	ANT.	MAX CAP	CHECK	—	—
6	600	ANT.	600	CHECK	350 uV/M	570 uV/M
7	1650	ANT	1650	CHECK	—	—

VIKING RM-542, RMK-543