

# VIKING Portable Electric Phonograph

**PMP-408**  
**PMP-408R**

## 4 SPEED 1 TUBE MANUAL

For Operation on 105-125 Volts A.C. Cycle as Marked

|                  |                          |           |
|------------------|--------------------------|-----------|
| SPECIFICATIONS : | Undistorted Power Output | 1.1 Watts |
|                  | Maximum Power Output     | 1.8 Watts |
|                  | Power Consumption        | 33 VA.    |
|                  | Tube                     | 25L6GT    |

## SERVICE REPLACEMENT PARTS LIST

### FINAL ASSEMBLY

|              |   |
|--------------|---|
| 12-15563-51  | Portable Phono Case - Green & White PMP 408 only  |
| 12-15563-52  | Portable Phono Case - Rust & White " " "          |
| 12-15563-53  | Portable Phono Case - Green & White PMP 408R only |
| 12-15563-54  | Portable Phono Case - Rust & White " " "          |
| 13-44-02     | Amplifier Curtain                                 |
| 13-29-03     | Motor Board For Changer                           |
| 16-120023-01 | Turntable BSR                                     |
| 16-120024-01 | Tone Arm & Cartridge Assembly                     |
| 16-250004-02 | TC8H BSR Cartridge                                |
| 16-120017-01 | LP Sapphire Needle                                |
| 16-120017-02 | 78 rpm Sapphire Needle                            |
| 16-210003-01 | Motor 4 Speed BSR 60 Cycle                        |
| 19-40005-01  | 4" PM Speaker 1.6 ohm                             |
| 53-8-02      | Knob - Off-On Volume                              |
| 53-380-01    | Viking Medallion                                  |
| 54-45-01     | Fire Barrier                                      |

### CHASSIS BASE ASSEMBLY - RIVETED

|             |   |
|-------------|---|
| 44-6-03     | Electrolytic 10 ufd X 25 volt<br>80-30 ufd X 150 volt |
| 24-80006-01 | Output Transformer                                    |
| 28-1-01     | Selenium Rectifier .65 ma                             |

### GENERAL CHASSIS COMPONENTS

|           |                              |
|-----------|------------------------------|
| 34-139-08 | Line Cord 8 ft. Ivory        |
| 41-14-01  | Control - Volume & AC Switch |
| 41-15-01  | Tone Control                 |

### CAUTION FOR SERVICEMEN

Any serviceman working with this unit when it is out of the cabinet should take special care not to come in contact with any ground connections.

When writing for Service Information, please quote model number and serial number. Always order service parts by part number. Part numbers are positive identification which ensures fast service and avoids unnecessary delays.

**THE T. EATON CO. LIMITED**  
**CANADA**

