



# VIKING RMK-369

## ALIGNMENT AND SENSITIVITY

SIGNAL GENERATOR MODULATED 30% AT 400 CYCLES

STEP	APPLY SIGNAL		THRU SERIES DUMMY	SET GANG AT	ADJUST FOR MAX. OUTPUT	NOMINAL SENSITIVITY FOR 50 MW. OUTPUT	NOMINAL SENSITIVITY FOR 100 MV. AT DIODE LOAD
	KC	TO					
1	455	12BA6 #1 PIN	.05	-	2ND I.F.	1800 $\mu$ V	3600 $\mu$ V
2	455	12BE6 #7 PIN	.05	MIN. CAP	1ST I.F. 2ND I.F.	63 $\mu$ V	150 $\mu$ V
3	1460	ANT.	*	1460 KC	OSC. TRIM. ANT. TRIM.	110 $\mu$ V./M.	245 $\mu$ V./M.
4	600	ANT.	*	600 KC	OSC. SLUG REPEAT STEP 3	220 $\mu$ V./M.	450 $\mu$ V./M.
5	535	ANT.	*	MAX. CAP.	CHECK ONLY		
6	1650	ANT.	*	MIN. CAP.	CHECK ONLY		

# VIKING RMK-369

