



Switch, S1, in extreme counter clockwise position (POS. 1)

Eico Model 950B

Resistance-Capacitance-Comparator Bridge

SELECTOR SWITCH POSITIONS

Sym.	Description	Sym.	Description	Sym.	Description
C1	cap., elec 8mfd-525V	P3	pot., 100KΩ, 4W	R9	res., 270KΩ, 1/2W
C2	cap., 200mfd, prec.	R1	res., 500Ω, 4W	R10	res., 10MΩ, 1/2W
C3	cap., .02mf, prec.	R2	res., 250K, 1/2W, 1%	R11	res., 2.2KΩ, 1W
C4	cap., 2mf, prec.	R3	res., 1MΩ, 1/2W	R12	res., 470K, 1/2W
C5, 6, 7	cap., .01mf-400V	R4	res., 20Ω, 1/2W, 1%	S1	switch, range
C8	cap., .25mf-600V	R5	res., 2KΩ, 1/2W, 1%	S2	switch, SPST, p/o P2
C9	cap., elec 4mfd-250V	R6	res., 200KΩ, 1/2W, 1%	V1	tube, 6X5
P1	pot., 10KΩ	R7	res., 3.3KΩ, 1W	V2	tube, 1629
P2	pot., 1KΩ w/SPST	R8	res., 68KΩ, 1W		

Pos. 1	10 mfd-5000 mfd
Pos. 2	.001 mfd-.5 mfd
Pos. 3	.1 mfd-50 mfd
Pos. 4	50 mfd-5000 mfd
Pos. 5	.5 Ω - 500 Ω
Pos. 6	50 Ω - 50K Ω
Pos. 7	5K Ω - 5M Ω
Pos. 8	5M Ω - 500M Ω
Pos. 9	Comparator
Pos. 10	Paper-Mica Test
Pos. 11	Electrolytic Test